



TX3141

Wireless Manual Call Point

Features and Benefits

- 433MHz Wireless Manual Call Point
- Low battery warning and LED status indicator
- Built-in addressable chip
- Aesthetically pleasing design and easy to install

Overview

The TX3141 Wireless Manual Call Point is designed for the use of raising an alarm manually once verification of a fire or emergency condition has been occurred through pressing the resettable glass. Built in 433MHz communication chipset to transmit the signal in real time to gateway, widely used in home automation, store security and other fire safety monitoring. The unit is creatively designed that complements modern housing lay-outs.

Technical Specification

Power Rating	
Battery Required	3 VDC (2 x 1.5 AA) batteries
Current Consumption	Standby 30μA, Alarm:8mA
Device	
Transmission Frequency	433MHZ
Transmission Distance	200 meters maximum (Open area)
LED Indicator	Single LED / 360-degree Visual/ Normal: Green LED Flash every 75 seconds Alarm: Red LED Steady Light Faulty: Yellow LED Flash every 45second

Material / Colour	ABS / Red
Diameter / Height	87mm x 85mm x 30mm
Weight	113g (with Battery)
Operating Temperature	-10°C to +55°C
Humidity	0 to 95% Relative Humidity, Noncondensing