

TX7300 Addressable Sounder and Strobe

## **Features and Benefits**

- EN54-3:2001+A1:2002 + A2:2006 Compliance
- Built-in MCU processor and digital addressing
- 17 tones Programmable sound output
- Programmable types such as Sounder-Strobe, Sounder or Strobe alone
- Programmable Evacuate or Pre-alarm/Evacuate signal
- Low and normal consumption mode
- One or Two addresses mode
- 10 Highlights LED status cluster
- Onsite Adjustable Parameters
- Loop or external power input
- Aesthetically pleasing design

Universal mounting with fix base for simple installation

### **Overview**

The TX7300 Addressable Sounder Strobe is alarm warning device used to notify persons in the vicinity of the occurrence fire emergency in order the person to take appropriate measures. The unit adopt multi-application device starting from the types, parameters and wiring layout in single unit. The TX7300 can change into different alarm warning types such as sounder-strobe type, sounder type or strobe type using programming tool. In addition, parameters can be configured according to the requirement which include alarm tone from 17 different tones, single address or dual address mode and also setting of power mode to low current consumption in a simple programming.

The unit manufactured base on the requirement of EN 54 part 3, European Standard. The unit is aesthetically pleasing with unobtrusive design that will complement modern building designs and its plug-in type assembles make installation and maintenance more convenient to the installer. The unit is compatible to the TX7004 Analogue Intelligent Fire Alarm Control Panel, produced by single manufacture T&A, to avoid addressable communication compatibility problem.

## **Technical Specification**

| Listed                    | LPCB / CE-CPR                        |  |
|---------------------------|--------------------------------------|--|
| Compliance                | EN54-3:2001+A1:2002 + A2:2006        |  |
| Power Rating              |                                      |  |
| Input Voltage             | Loop Power: 24VDC [18V to 27.5V]     |  |
| External PSU              | 24 VDC [20V to 27.5V]                |  |
| Typical Current           | Loop: Standby 0.6mA, Alarm:<br>1.5mA |  |
| Loop and<br>External PSU  | Standby 0.6mA, Alarm: 15mA           |  |
| Saving Current            | Standby 1.2mA, Alarm: 9mA            |  |
| Sounder<br>Strobe         |                                      |  |
| Sounder level<br>Pressure | 102 dBA at 1 meter / tone 14         |  |
| Tone                      | 17 Tones (refers to Manual)          |  |

| Address<br>Sequence             | Single Address: Evacuate tone                                       |
|---------------------------------|---|
| Protocol/<br>Addressing         | T&A, Value range from 1 to 254,<br>dual address1st Alert / 2nd Evac |
| Strobe Light                    | 10 Highlights LED   |
| Material /<br>Colour            | ABS / RED Glossy finishing  |
| Dimension /<br>Height           | Diameter 110 mm / 39.6 (with<br>Base)                               |
| Weight                          | 176g (with Base), 110g (Without<br>Base)                            |
| Class                           | IP30  |
| Operating<br>Temperature        | -10°C to +50°C  |
| Ingress<br>Protection<br>Rating | IP21  |
| Humidity                        | 0 to 95% Relative Humidity,<br>Non-condensing                       |

# Sounder and Wiring Details

